

TRULUX™ RGB / RGB+WW Custom Cut Cheat Sheet

With our easy to use cheat sheet, we've done most of the guess work for you! If your application length falls between specified cuttable lengths, we recommend rounding to the nearest cut increment for optimum efficiency. Three foot lead wire comes standard, but you can also specify additional feet if needed. Be sure to consider voltage drop when determining tape light and lead wire length.

TRULUX™ RGB



4.6W per ft / Up to 370Lm per ft
Cuttable 3.94" / Max Run 22 ft

Feet	Inches	Feet	Inches
0ft	3.94"	11ft	5.8"
0ft	7.9"	11ft	9.7"
0ft	11.8"	12ft	1.7"
1ft	3.8"	12ft	5.6"
1ft	7.7"	12ft	9.5"
1ft	11.6"	13ft	1.5"
2ft	3"	13ft	5.4"
2ft	7.5"	13ft	9.4"
2ft	11.4"	14ft	1.3"
3ft	3.4"	14ft	5.2"
3ft	7.3"	14ft	9.2"
3ft	11.2"	15ft	1.1"
4ft	3.2"	15ft	5"
4ft	7.1"	15ft	9"
4ft	11.1"	16ft	0.9"
5ft	3"	16ft	4.8"
5ft	6.9"	16ft	8.8"
5ft	10.9"	17ft	0.7"
6ft	2.8"	17ft	4.7"
6ft	6.7"	17ft	8.6"
6ft	10.7"	18ft	0.5"
7ft	2.6"	18ft	4.5"
7ft	6.6"	18ft	8.4"
7ft	10.5"	19ft	0.3"
8ft	2.4"	19ft	4.3"
8ft	6.4"	19ft	8.2"
8ft	10.3"	20ft	0.2"
9ft	2.2"	20ft	4.1"
9ft	6.2"	20ft	8"
9ft	10.1"	21ft	0"
10ft	2"	21ft	3.9"
10ft	6"	21ft	7.8"
10ft	9.9"	21ft	11.8"
11ft	1.9"		

TRULUX™ RGB+WW



4.6W per ft / Up to 370Lm per ft
Cuttable 6.56" / Max Run 22 ft

Feet	Inches	Feet	Inches
0ft	6.56"	11ft	6.1"
1ft	1.1"	12ft	0.6"
1ft	7.7"	12ft	7.2"
2ft	2.3"	13ft	1.8"
2ft	8.9"	13ft	8.4"
3ft	3.4"	14ft	2.9"
3ft	10"	14ft	9.5"
4ft	4.6"	15ft	4.1"
4ft	11.2"	15ft	10.7"
5ft	5.7"	16ft	5.2"
6ft	0.3"	16ft	11.8"
6ft	6.9"	17ft	6.4"
7ft	1.5"	18ft	1"
7ft	8"	18ft	7.5"
8ft	2.6"	19ft	2.1"
8ft	9.2"	19ft	8.7"
9ft	3.8"	20ft	3.3"
9ft	10.3"	20ft	9.8"
10ft	4.9"	21ft	4.4"
10ft	11.5"	21ft	11"

Lead Wire and Voltage Drop

All of our RGB/RGB+WW tape light includes a 3ft SPT1 22AWG lead wire that is soldered to the end of the tape and sealed with shrink tubing. Please see our voltage drop chart for more information on acceptable tape and lead wire lengths.

